

Communication FM ceramic filters: (CS455 / CS450 SMD ceramic filter -6 sub-prime)



Size: (11.5 * 7.5 * t) / (6.0 * 7.5 * t)

Features:

Suitable for automatic installation

Strong mechanical strength

A wide bandwidth and high selectivity

Suitable for car radios and various radio frequency bands

CS455 / CS450 series ceramic filters -6 sub-prime technical indicators

Model	Center frequency	6 db bandwidth	50 (40) dB bandwidth	Stopband consumption	Passband	Insertion Loss	Input / Output Impedance
CS455B6	455	± 13.5	± 30.0	45	2	4	1000
CS455C6	455	± 12.5	± 25.0	45	3	4	1000
CS455D6	455	± 10.0	± 20.0	45	3	4	1500
CS455E6	455	± 7.5	± 15.0	45	3	4	1500
CS455F6	455	± 6.0	± 12.5	45	3	4	1500
CS455G6	455	± 4.5	± 10.0	45	3	4	1500
CS455H6	455	± 3.0	± 9.0	45	3	4	1500